

LINK-80 Operator's Guide

Appendix E Supplement

This supplement describes the multi-line command feature incorporated into LINK-80 in version 1.3 or later.

E.2.0. MULTI-LINE COMMANDS

If a command does not fit on a single line (126 characters), the command may be extended by terminating the command line with an ampersand (&). The ampersand may appear after any character of the command, and need not follow a file name. LINK-80 responds with an asterisk (*) on the next line. At this point the command line may be continued. Any number of lines ending with an ampersand may be entered. The last line of the command is terminated with a carriage return. Note that XSUB may be used to submit multi-line LINK-80 commands.

Example:

```
A>link main, iomod1, iomod2, iomod3, iomod4, iomod5,&  
LINK 1.3  
*lib1[s], lib2[s], lib3[s], lib4&  
*[s], lastmod[p2000&  
*,d200]
```

```
(. . .symbol table and memory map. . .)
```

```
A>
```